

80i-110s 交/直流电流钳



主要特性

- Current Range: 0.1 to 100A DC or 0.1 to 100A AC
- Basic Accuracy (DC to 1kHz):
 - 100mV/A setting: 50mA to 10A +/- 3% of reading + 50mA
 - 10mV/A setting: 50mA to 40A +/- 4% of reading + 50mA
 - 40A to 80A +/- 12% of reading + 50mA
 - 80 to 100A +/- 15% of reading
- Output Signal: 10A range: 100mV/A | 100A range: 10mV/A
- Bandwidth: 1Hz to 20kHz
- Working Voltage: 600V AC rms
- Maximum Conductor Size: 11.8 mm (.46 inch) diameter
- Safety Rating: IEC 1010 and CSA-C22.2 No. 1010-1 Installation Category II, Working Voltage 600V

产品概述: 80i-110s 交/直流电流钳

80i-110交/直流电流钳与任何福禄克示波表、功率谐波分析仪、万用表或其他电压测量工具兼容，其具有以下特点：BNC输入连接器或如果使用仪表，使用适配器PM9081/ 001将香蕉插头转换为BNC连接器。

产品规格: 80i-110s 交/直流电流钳

型号



Fluke 80i 110s
交/直流电流钳

Fluke. 让您的工作畅通无阻。

福禄克测试仪器（上海）有限公司 电话：400-810-3435 ©2025 福禄克公司
04/2025

北京福禄克世禄仪器维修和服务有限公司 电
话：400-615-1563

未经许可，本文档禁止修改

福禄克测试仪器（上海）有限公司上海维修中心 电
话：021-54402301, 021-54401908分机269

福禄克测试仪器（上海）有限公司深圳第一特约维修点
电话：0755-86337229